

The title of the document, 'FS 100G Optics-to-Optics Interoperability Matrix', is displayed in white text. A blue circle is positioned to the left of the first 'F' in 'FS'.

Interoperability

FS transceivers and cables are based on industry standards and/or Multi-Source Agreements (MSA) and therefore interoperable with the relevant standards and MSA transceivers. Guidance on the interoperability of the FS 100G transceivers is detailed in Tables 1.

Table 1 shows the interoperability of 100G modules.

Table 1. 100G Transceiver Interoperation and Link Reach

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-SR4-100G	QSFPDD-2SR4-200G	Breakout MMF patchcord: MTP/MPO-24 to 2X MTP/MPO-12. For cabling guides, see https://www.fs.com/products/69995.html	RS-FEC: 100m	Y
	QSFP-SR4-100G	-	RS-FEC: 70m (OM3), 100m (OM4)	-
	QSFP-SR4-100G-I	-	RS-FEC: 70m (OM3), 100m (OM4)	-
	QSFP-ESR4-100G	-	RS-FEC: 70m (OM3), 100m (OM4)	-
	SFP28-25GSR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 70m (OM3), 100m (OM4)	Y
	SFP28-25GESR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 70m (OM3), 100m (OM4)	Y
	SFP-10/25GCSR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 70m (OM3), 100m (OM4)	Y
QSFP-PSM4-100G	QSFP-PSM4-100G	-	RS-FEC: 500m	-
	QSFP28-PSM4-100G	-	RS-FEC: 500m	-
	SFP28-25GLR-31	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	SFP-10/25GLR-31	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-PSM4-100G	SFP-25GLRL-31-I	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	S28-25GLR20-31-I	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	SFP-10/25LR-31-I	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
QSFP-DR-100G	OSFP-DR4-400G-Si	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QDD-DR4-400G-Si	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QSFPDD-XDR4-400G	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QSFPDD-PLR4-400G	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QSFP-DR-100G	-	RS-FEC: 500m	-
	QSFP-FR-100G	-	RS-FEC: 500m	-
	QSFP-LR-100G	-	RS-FEC: 500m	-
QSFP-FR-100G	OSFP-DR4-400G-Si	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QDD-DR4-400G-Si	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QSFPDD-XDR4-400G	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 2km	Y

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-FR-100G	OSFP-DR4-400G-Si	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QDD-DR4-400G-Si	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QSFPDD-XDR4-400G	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 2km	Y
	QSFPDD-PLR4-400G	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 2km	Y
	QSFP-FR-100G	-	RS-FEC: 2km	-
	QSFP-DR-100G	-	RS-FEC: 500m	-
	QSFP-LR-100G	-	RS-FEC: 2km	-
QSFP-CWDM4-100G	QSFP-CWDM4-100G	-	RS-FEC: 2km	-
	QSFP-4W10-100G	-	RS-FEC: 2km	-
QSFP-LR-100G	QSFPDD-PLR4-400G	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 10km	Y
	OSFP-DR4-400G-Si	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QSFPDD-XDR4-400G	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 2km	Y
	QDD-DR4-400G-Si	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	QSFP-LR-100G	-	RS-FEC: 10km	-
	QSFP-DR-100G	-	RS-FEC: 500m	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-LR-100G	QSFP-FR-100G	-	RS-FEC: 2km	-
QSFP-LR4-100G	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	No FEC: 10km	-
	QSFP-ZR4-100G	-	No FEC: 10km	-
	QSFP-4W40-100G-E	-	No FEC: 10km	-
	QSFP-4W20-100G-I	-	No FEC: 10km	-
	QSFP-4W40-100G-I	-	No FEC: 10km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	No FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
QSFP-LR4-100G-I	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	No FEC: 10km	-
	QSFP-ZR4-100G	-	No FEC: 10km	-
	QSFP-4W40-100G-E	-	No FEC: 10km	-
	QSFP-4W20-100G-I	-	No FEC: 10km	-
	QSFP-4W40-100G-I	-	No FEC: 10km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	No FEC: 10km	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-LR4-100G-I	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
QSFP-ER4L-100G	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	RS-FEC: 40km	-
	QSFP-ZR4-100G	-	RS-FEC: 40km	-
	QSFP-4W40-100G-E	-	RS-FEC: 40km	-
	QSFP-4W20-100G-I	-	RS-FEC: 20km	-
	QSFP-4W40-100G-I	-	RS-FEC: 40km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	RS-FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
QSFP-ZR4-100G	QSFP-ER4L-100G	-	RS-FEC: 40km	-
	QSFP-ZR4-100G	-	RS-FEC: 80km	-
	QSFP-4W40-100G-E	-	RS-FEC: 40km	-
	QSFP-4W20-100G-I	-	RS-FEC: 20km	-
	QSFP-4W40-100G-I	-	RS-FEC: 40km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-ZR4-100G	CFP-ER4-100G	-	RS-FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
QSFP-ESR4-100G	QSFPDD-2SR4-200G	Breakout MMF patchcord: MTP/MPO-24 to 2X MTP/MPO-12. For cabling guides, see https://www.fs.com/products/69995.html	RS-FEC: 100m	Y
	QSFP-ESR4-100G	-	RS-FEC: 200m (OM3), 300m (OM4)	-
	QSFP-SR4-100G	-	RS-FEC: 70m (OM3), 100m (OM4)	-
	QSFP-SR4-100G-I	-	RS-FEC: 70m (OM3), 100m (OM4)	-
	SFP28-25GSR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 200m (OM3), 300m (OM4)	Y
	SFP28-25GESR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 200m (OM3), 300m (OM4)	Y
	SFP-10/25GCSR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 200m (OM3), 300m (OM4)	Y
QSFP-BX20-100G	QSFP-BX20-100G	-	RS-FEC: 20km	-
QSFP-BIDI-100G	QSFP-BIDI-100G	-	RS-FEC: 100m	-
QSFP28-SRBD-100G	QSFP28-SRBD-100G	-	RS-FEC: 100m	-
QSFP-SR4-100G-I	QSFPDD-2SR4-200G	Breakout MMF patchcord: MTP/MPO-24 to 2X MTP/MPO-12. For cabling guides, see https://www.fs.com/products/69995.html	RS-FEC: 100m	Y
	QSFP-SR4-100G	-	RS-FEC: 70m (OM3), 100m (OM4)	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-SR4-100G-I	QSFP-SR4-100G-I	-	RS-FEC: 70m (OM3), 100m (OM4)	-
	SFP28-25GSR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 70m (OM3), 100m (OM4)	Y
	SFP28-25GESR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 70m (OM3), 100m (OM4)	Y
	SFP-10/25GCSR-85	Breakout MMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68047.html	RS-FEC: 70m (OM3), 100m (OM4)	Y
QSFP-4W10-100G	QSFP-CWDM4-100G	-	RS-FEC: 2km	-
	QSFP-4W10-100G	-	RS-FEC: 10km	-
QSFP-4W40-100G-E	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	RS-FEC: 40km	-
	QSFP-ZR4-100G	-	RS-FEC: 40km	-
	QSFP-4W40-100G-E	-	RS-FEC: 40km	-
	QSFP-4W20-100G-I	-	RS-FEC: 20km	-
	QSFP-4W40-100G-I	-	RS-FEC: 40km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	RS-FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
QSFP-4W20-100G-I	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-4W20-100G-I	QSFP-ER4L-100G	-	RS-FEC: 20km	-
	QSFP-ZR4-100G	-	RS-FEC: 20km	-
	QSFP-4W40-100G-E	-	RS-FEC: 20km	-
	QSFP-4W20-100G-I	-	RS-FEC: 20km	-
	QSFP-4W40-100G-I	-	RS-FEC: 20km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	RS-FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
QSFP-4W40-100G-I	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	RS-FEC: 20km	-
	QSFP-ZR4-100G	-	RS-FEC: 20km	-
	QSFP-4W40-100G-E	-	RS-FEC: 20km	-
	QSFP-4W20-100G-I	-	RS-FEC: 20km	-
	QSFP-4W40-100G-I	-	RS-FEC: 40km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	RS-FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
DWDM2-Q28100G-80	DWDM2-Q28100G-80	-	No FEC: 80km	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP28-PSM4-100G	QSFP-PSM4-100G	-	RS-FEC: 500m	-
	QSFP28-PSM4-100G	-	RS-FEC: 2km	-
	SFP28-25GLR-31	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	SFP-10/25GLR-31	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	SFP-25GLRL-31-I	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	S28-25GLR20-31-I	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
	SFP-10/25LR-31-I	Breakout SMF patchcord: MTP/MPO-12 to 4X LC Duplex. For cabling guides, see https://www.fs.com/products/68048.html	RS-FEC: 500m	Y
QSFP-LR4-100GM	QSFP-LR4-100GM	-	No FEC: 10km	-
	QSFP-ELR4-100GM	-	No FEC: 10km	-
	QSFP-ER4-100GM	-	No FEC: 10km	-
QSFP-ELR4-100GM	QSFP-LR4-100GM	-	No FEC: 10km	-
	QSFP-ELR4-100GM	-	No FEC: 20km	-
	QSFP-ER4-100GM	-	No FEC: 20km	-
QSFP-ER4-100GM	QSFP-LR4-100GM	-	No FEC: 10km	-
	QSFP-ELR4-100GM	-	No FEC: 20km	-
	QSFP-ER4-100GM	-	RS-FEC: 40km	-
QSFP-SR4-100G	QSFP-SR4-100G	-	RS-FEC: 70m (OM3), 100m (OM4)	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
QSFP-PSM4-100G(IB)	QSFP-PSM4-100G(IB)	-	RS-FEC: 500m	-
QSFP-CWDM4-100G	QSFP-CWDM4-100G	-	RS-FEC: 2km	-
QSFP-LR4-100G	QSFP-LR4-100G	-	No FEC: 10km	-
CFP-LR4-100G	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	No FEC: 10km	-
	QSFP-ZR4-100G	-	No FEC: 10km	-
	QSFP-4W40-100G-E	-	No FEC: 10km	-
	QSFP-4W20-100G-I	-	No FEC: 10km	-
	QSFP-4W40-100G-I	-	No FEC: 10km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	No FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
CFP-ER4-100G	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	RS-FEC: 10km	-
	QSFP-ZR4-100G	-	RS-FEC: 10km	-
	QSFP-4W40-100G-E	-	RS-FEC: 10km	-
	QSFP-4W20-100G-I	-	RS-FEC: 10km	-
	QSFP-4W40-100G-I	-	RS-FEC: 10km	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
CFP-ER4-100G	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	RS-FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
CXP-SR10-100G	CXP-SR10-100G	-	RS-FEC: 150m	-
	SFP-10GSR-85	Breakout MMF patchcord: MTP/MPO-24 to 10X LC Duplex. For cabling guides, see https://www.fs.com/products/31097.html	No FEC: 100m (OM3), 150m (OM4)	Y
	SFP-10GSR-85-I	Breakout MMF patchcord: MTP/MPO-24 to 10X LC Duplex. For cabling guides, see https://www.fs.com/products/31097.html	No FEC: 100m (OM3), 150m (OM4)	Y
CFP-SR10-100G	CFP-SR10-100G	-	RS-FEC: 150m	-
	SFP-10GSR-85	Breakout MMF patchcord: MTP/MPO-24 to 10X LC Duplex. For cabling guides, see https://www.fs.com/products/31097.html	No FEC: 100m (OM3), 150m (OM4)	Y
	SFP-10GSR-85-I	Breakout MMF patchcord: MTP/MPO-24 to 10X LC Duplex. For cabling guides, see https://www.fs.com/products/31097.html	No FEC: 100m (OM3), 150m (OM4)	Y
CFP2-LR4-100G	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	No FEC: 10km	-
	QSFP-ZR4-100G	-	No FEC: 10km	-
	QSFP-4W40-100G-E	-	No FEC: 10km	-
	QSFP-4W20-100G-I	-	No FEC: 10km	-
	QSFP-4W40-100G-I	-	No FEC: 10km	-
	CFP-LR4-100G	-	No FEC: 10km	-

Transceiver Interoperability				
Transceiver Product ID	Transceiver/Standard	Notes	Interop Reach (up to)	Breakout Patchcord Required
CFP2-LR4-100G	CFP-ER4-100G	-	No FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-
CFP4-LR4-100G	QSFP-LR4-100G	-	No FEC: 10km	-
	QSFP-LR4-100G-I	-	No FEC: 10km	-
	QSFP-ER4L-100G	-	No FEC: 10km	-
	QSFP-ZR4-100G	-	No FEC: 10km	-
	QSFP-4W40-100G-E	-	No FEC: 10km	-
	QSFP-4W20-100G-I	-	No FEC: 10km	-
	QSFP-4W40-100G-I	-	No FEC: 10km	-
	CFP-LR4-100G	-	No FEC: 10km	-
	CFP-ER4-100G	-	No FEC: 10km	-
	CFP2-LR4-100G	-	No FEC: 10km	-
	CFP4-LR4-100G	-	No FEC: 10km	-

Shenzhen (China)

Address: 24F, Yingfeng Center, Haitian 2nd Rd,
Nanshan District, Shenzhen
Tel: +86 400 865 2852
Email: sales@feisu.com

Delaware (United States)

Address: 380 Centerpoint Blvd, New Castle,
DE 19720, United States
Tel: +1 (888) 468 9910
Email: us@fs.com

Munich (Germany)

Address: NOVA Gewerbepark Building 7, Am
Gfild 7,85375 Neufahrn bei Munich, Germany
Tel: +49 (0) 8131 377 3008
Email: de@fs.com

Singapore

Address: 30A Kallang Pl, #11-10/11/12 Singapore
339213
Tel: +65 3138 1992
Email: sg@fs.com

Wuhan (China)

Address: 9-14F, Optical Valley Software Park
A7, Guanshan Ave, Wuhan
Tel: +86 400 865 2852
Email: sales@feisu.com

Birmingham (United Kingdom)

Address: Regus Edmund House, 12-22 Newhall
Street, Birmingham, B3 3AS
Tel: +44 (0) 121 726 4775
Email: uk@fs.com

Melbourne (Australia)

Address: 57-59 Edison Rd, Dandenong South,
VIC 3175, Australia
Tel: +613 5909 9990

Email: au@fs.com

Tokyo (Japan)

Address: JS Progress Building, 4-1-23 Heiwajima,
Ota-ku, Tokyo 〒143-0006
Tel: +813 6897 9438

Email: jp@fs.com

FS has several offices around the world. Addresses, phone numbers are listed on the FS Website at https://www.fs.com/contact_us.html
FS and FS logo are trademarks or registered trademarks of FS in the U.S. and other countries.